

120V AC CIRCUIT BREAKER FINDER

W/FLASHLIGHT, NCVT & GFCI RECEPTACLE TESTER



61-535 120V AC CIRCUIT BREAKER FINDER

- cULus Certified (UL 1436, CSA C22.2 No. 160), CAT II 150V
- Quickly and easily identifies circuit breakers/fuses without disrupting power on energized 120V AC circuits
- Clear Visual and Audible indicators (audible signal can be muted)
- NCVT in receiver tip indicates presence of AC voltage between 80-300V AC
- Flashlight in receiver operates independently of the tester functions and can be used to illuminate work area
- Transmitter tests outlet wiring configurations (indicated via Green/Red LEDs) and tests GFCIs
- Receiver powers off automatically after 5 minutes of non-use to conserve battery life

Narrower Tip
improves breaker identification accuracy

LED Flashlight
operates independently and illuminates work area

Transmitter
sends a signal over the conductors when connected to an energized circuit. It also identifies the presence of power and indicates correct/incorrect wiring conditions via illuminated green and red LED's. A GFCI test light illuminates when the GFCI Test button is pressed, indicating the activation of the GFCI test. The GFCIs will trip if they are functioning properly



NOTE: Receptacle MUST be properly grounded for the GFCI test to work properly.

NOTE: The transmitter works on LIVE/Energized circuits only



Receiver
powers off automatically after five minutes of non-use to conserve battery life

Lanyard Mount

NCVT
in receiver tip indicates presence of AC voltage between 80-300 volts (visual flashing red LEDs & audible indicators)



Receiver
reads the transmitter's signal and identifies the breaker/finder energizing the circuit by illuminating a flashing green LED and emitting beeps once it determines the breaker/fuse with the strongest signal.

LED Flashlight

Audible Defeat
for noise sensitive areas

ON/OFF
toggles between circuit breaker finding and NCVT functions (default is circuit breaker finding)



SCAN
to learn more



THE ELECTRICIAN'S
CHAMPION™



120V AC CIRCUIT BREAKER FINDER


W/FLASHLIGHT, NCVT & GFCI RECEPTACLE TESTER

61-535
Transmitter

61-535
Receiver



SCAN
to learn more



CIRCUIT BREAKER FINDER SELECTION GUIDE



**REPLACED BY
THE ENHANCED
AND
ERGONOMIC
61-535**



| TRANSMITTER FEATURES | 61-535 | 61-534 | 61-532 |
|--|-------------------------------|-------------------------------|-------------------------------|
| CAT Rating (Safety) | CAT II 150V | CAT II 300V | CAT II 300V |
| Listing | UL 1436, CSA C22.2 No. 160 | UL 1436, CSA C22.2 No. 160 | UL 1436, CSA C22.2 No. 160 |
| Line Voltage | Line Powered (120V AC) | Line Powered (120V AC) | Line Powered (120V AC) |
| Supply Frequency | 60Hz | 47-63Hz | 47-63Hz |
| Weight | 28.35g (approx.) | 50g (approx.) | 50g (approx.) |
| Flashlight | ✓ | — | — |
| NCVT | ✓ | — | — |
| Power Consumption | 1.5W max. @ 120V AC | 200mW max. @ 120V AC | 200mW max. @ 120V AC |
| Correct/Wiring Fault/Polarity Indications | ✓ | ✓ | — |
| GFCI Trip/Test | ✓ | ✓ | — |
| GFCI Trip Test Indicator | ✓ | — | — |
| RECEIVER FEATURES | 61-535 | 61-534 | 61-532 |
| Visual and Audible Indicators | ✓ | ✓ | ✓ |
| Low Battery Indication | ✓ | ✓ | ✓ |
| Auto Power Off (after no activity) | (after 5 minutes) | (after 10 minutes) | (after 10 minutes) |
| Battery Type | 9V | 9V | 9V |
| Weight | 85g (w/o battery) | 85g (w/o battery) | 85g (w/o battery) |
| Warranty | 2-Year* | 2-Year* | 2-Year* |
| ACCESSORIES | 61-535 | 61-534 | 61-532 |
| Light Socket, 3 to 2-Prong Adapters, Alligator Clips | TL-532A | TL-532A | TL-532A |

* Visit www.idealind.com for warranty details.

Specifications are subject to change without notice.

P-6070 (02-23)
©2023 IDEAL INDUSTRIES, INC.

IDEAL CUSTOMER SERVICE:
orderdesk@idealindustries.com
1-800-824-3325
www.idealind.com

THE ELECTRICIAN'S
CHAMPION™

