

120V AC GFCI RECEPTACLE TESTER

UPGRADED TECHNOLOGY AND INDUSTRIAL DESIGN



61-502 120V AC GFCI RECEPTACLE TESTER

- cULus Certified (UL 1436, CSA C22.2 No. 160) for 120V AC circuits
- Detects common wiring problems in receptacles
- Confirms operation of GFCI protective devices



Trips GFCI's
in circuit by pressing the black button



Test Light
will turn on, indicating the activation of the GFCI test and the GFCIs will trip if they are functioning properly




Simply plug into outlet and compare which lights are lit to the legend on the tester

LEGEND

Indicates a correct wiring condition as well as the following wiring faults:

- open ground
- reverse polarity
- open hot
- open neutral
- hot & gnd. rev.
- hot on neutral with hot open
- hot and ground reversed
- hot on neutral with hot open



NOTE: Receptacle MUST be properly grounded for the GFCI test to work properly.

RECEPTACLE TESTER SPECIFICATIONS



DISCONTINUED



Replaced by 61-502

FEATURES	61-502	61-517	61-051	61-035	61-501
CAT Rating (Safety)	CAT II 150V	CAT II 150V	—	—	—
Listing	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160	UL 1436, CSA C22.2 No. 160
Voltage Rating	120V AC	120V AC	120V AC	120V AC	120V AC
Correct/Wiring Fault/Polarity Indications	✓	✓	✓	✓	✓
GFCI Trip	✓	✓	✓	—	✓
GFCI Trip Test Indicator	✓	✓	—	—	—
Made in the U.S.A.	—	—	✓	✓	—
Neon Lamps	✓	LED's	✓	✓	✓
LCD Display (Voltage)	—	✓	—	—	—
Warranty	2-Year*	2-Year*	2-Year*	2-Year*	1-Year*

* Visit www.idealind.com for warranty details.

Specifications are subject to change without notice.

P-6071 (02-23)

©2023 IDEAL INDUSTRIES, INC.

IDEAL CUSTOMER SERVICE:
orderdesk@idealindustries.com
1-800-824-3325
www.idealind.com

THE ELECTRICIAN'S
CHAMPION™

